



Electrical Connector Maintenance Kit (4 pieces)

This kit is designed to help you keep electrical contacts free of corrosion. It's easy to use:

1. Apply a small droplet (a little goes a long way) of the DeOxit contact cleaner on the electrical contact you wish to clean.
2. With the burnishing tool, gently scrub the contact until the metal has turned from dull green-brown or black, to a brighter yellow/brown. You'll notice some of the corrosion on your burnishing tool. You can clean that up with a rag.
3. Once the contacts are clean, apply a tiny dab of the dielectric grease, to lubricate and protect the contacts. Plug in the cord once or twice to spread the grease around.

ABOUT THE 7-WAY TRAILER PLUG

The 7-way cord contains all the wires needed for the trailer's lights (clearance, brake, turn), brakes, and power to keep the battery charged while towing. All Airstreams since 1989 have used the same wire arrangement, shown in the diagram. Earlier trailers

